

SLR-1000

Sound Level Meter

Digital Sound Level Meter for measuring and recording industrial, automotive and ambient noise levels in decibels. Features wide measuring range and adjustable sensitivity for increased accuracy in any application environment.

Features:

- Portable and lightweight
- 50 record memory
- Max hold function
- Alarm function
- Low battery indicator
- Bluetooth® wireless data output (Optional extra)

Specifications:

Display: 10mm LCD

Frequency range: 31.5Hz ~ 8kHz

Measurement Ranges:

LP: 30~130dB (A)

35~130dB (C)

35~130 dB (F)

Leq: 30-130dB

LN: 0 ~ 100%

Resolution: 0.1dB

Accuracy: ±1dB

Function: LP , Leq ,LN.

Memory: 50 readings

Power Supply: 4 x AAA

Size: 236 x 63 x 26mm

Weight: 170 gm

Standard Delivery:

Tester, Foam sensor protection sock, Batteries, User manual

